

# **TRANSITION STRIPS**

MJ43 - 41mm Seamless

**Transition Ramp** 

For transition between

Adjustable

2.1 - 5.8mm

Adjustable

Height 5.8 - 9.5mm

Adjustable

Height - 12.3mm

Height

floor finishes with up


to 5mm height variance.

MJ43 with MJ40

MJ43 with MJ405

MJ43 with MJ41


## MJ42 - 37mm Seamless Transition Strip






For transition between floor finishes without height variance.

## **Multi-Height Trim Bases**







MJ42 with MJ41 Adjustable Height 12-15.7mm


## **Product specifications**


#### Product code: **MJ42 MJ43 MJ44 MJ40** MJ405 **MJ41 Overall length:** 3.3m 3.3m 3.3m 3.3m 3.3m 3.3m Overall width: 37mm 40mm 23mm 20mm 20mm 20mm **Overall height:** 6.5mm 7.65mm 6.5mm 6.3mm 9.8mm 12.8mm Anodised finishes: Black (BL) $\checkmark$ $\checkmark$ $\checkmark$ Bronze (BR) $\checkmark$ $\checkmark$ $\checkmark$ Champagne $\checkmark$ (CH) Silver (SI) $\checkmark$ $\checkmark$ Mill (M) - Not $\checkmark$ $\checkmark$ anodised 10 20 Lengths per carton: 10 10 10 10

## Page 1 of 2


WWW.MJSFLOORCOVERINGS.COM.AU

### MJ44 – Multi-Height L Shape Trim





For use on perimeters of flooring installations.



MJ44 with MJ405 Adjustable Height

<b>,</b>		 >	
B	3		Ŧ
Ч	ų		L
۲		 	t
_		 ·	

MJ44 with MJ41				
	Adjustable			
	Height			
	12 - 15.7mm			
	t			



# **TRANSITION STRIPS**

## Installation instructions

Cut the Transition Strip and Multi-Height Trim Base to required length. Fix the Multi-Height Trim Base in position using MJS GF400 construction adhesive, once adhesive is cured then install your floor coverings.

Install the Transition Strip by aligning the channel above the Multi-Height Trim Base, carefully tap down the Transition strip using a hardwood block with non marking surface and a hammer to lock in place.

**Safety statement:** When cutting or drilling aluminium we recommend the use of safety glasses and gloves.

